Supported device compatibility with RIVAGE PM/DM7/CL/QL/DM3/TF

Update: January, 2026

Manufacturer	Product	Device IDs	RIVAGE PM				DM7		CL/QL		DM3		TF	
			per HY card		per system									
			Mountable devices	Controllable devices	Mountable devices *1	Controllable devices *1	Mountable devices	Controllable devices	Mountable devices	Controllable devices	Mountable devices	Controllable devices (INPUT)	Mountable devices	Controllable devices (INPUT)
Audinate	Dante Virtual Soundcard	N/A	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Audinate	Dante-MY16-AUD	4096	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Audinate	Dante-MY16-AUD2	4096	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Aviom	D400	16	16	N/A	16	N/A	16	N/A	16	N/A	N/A	N/A	N/A	N/A
Aviom	D800	16	16	N/A	16	N/A	16	N/A	16	N/A	N/A	N/A	N/A	N/A
d&b audiotechnik	DS10	255	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Digital Audio Labs	LIVEMIX EXP, EXP2, EXP2 REV C, PRO	16	24	N/A	48	N/A	16	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Focusrite	RedNet 4	32	24	24	32	32	24	24	24	8	N/A	N/A	N/A	N/A
Focusrite	RedNet MP8R	32	24	24	32	32	24	24	24	3 (*7)	N/A	N/A	N/A	N/A
Nexo	DTD	4096	N/A	N/A	N/A	N/A	N/A	N/A	24	N/A	N/A	N/A	N/A	N/A
Nexo	DME10	254	24	24	48	48	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Nexo	NXAMP4x1mk2	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
Nexo	NXAMP4x2mk2	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
Nexo	NXAMP4x4, NXAMP4x1	4096	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Nexo	NXAMP4x4mk2	4096	24	24	48	48	24	24	24	8	N/A	N/A	N/A	N/A
Neutrik	NA2-IO-DPRO	32	24	24	32	32	24	24	24	8	N/A	N/A	N/A	N/A
Rupert Neve Designs	RMP-D8	4096	24	24	48	48	24	24	24	8	N/A	N/A	N/A	N/A
Sennheiser	EM 6000	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
Shure	AD4D, AD4Q	4096	24	24	48	24 (*3)	24	24	24	24	N/A	N/A	N/A	N/A
Shure	AXT400	4096	24	24	48	24 (*3)	24	24	24	24	N/A	N/A	N/A	N/A
Shure	QLXD4	4096	24	24	48	24 (*3)	24	24	24	24	N/A	N/A	N/A	N/A
Shure	ULXD4, ULXD4D, ULXD4Q	4096	24	24	48	24 (*3)	24	24	24	24	N/A	N/A	N/A	N/A
Shure	SLXD4, SLXD4D, SLXD4Q+, SLXD4QDAN+	4096	24	24	48	24 (*3)	24	24	N/A	N/A	N/A	N/A	N/A	N/A
Sony	DWR-R03D	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
StageTec	XDIP	4096	N/A	N/A	N/A	N/A	N/A	N/A	24	4	N/A	N/A	N/A	N/A
Yamaha	DM7, DM7 Compact (*5)	4	4	4	4	4	4	4	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	DM3	32	24	24	32	32	24	24	32	8	N/A	16	N/A	N/A
Yamaha	CL1, CL3, CL5 (*5)	4	4	N/A	4	N/A	4	N/A	4	N/A	N/A	N/A	N/A	N/A
Yamaha	DANTE-ACCELELATOR	4096	12	N/A	48	N/A	12	N/A	12	N/A	N/A	N/A	N/A	N/A
Yamaha	DSP-R10-HY1-HY4, CSD-R7-HY1-3, DSP-RX-HY1-4, DSP-RX-EX-HY1-4 (*5)	4	4	N/A	4	N/A	4	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	DXS15XLF-D, DXS18X-LF-D, DZR10-D, DZR12-D, DZR15-D, DZR315-D	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	8
Yamaha	HY144-D, HY144-D-SRC	4096	24	N/A	48	N/A	24	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	MRX7-D, MTX3, MTX5-D	64	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
Yamaha	DME7	254	24	N/A	48	N/A	24	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	NUAGE-IO16A, NUAGE-IO16D, NUAGE-IO8A8D	16	16	N/A	16	N/A	16	N/A	16	N/A	N/A	N/A	N/A	N/A
Yamaha	PC-D/DI series	4096	24	24	48	48	24	24	24	24	N/A	N/A	N/A	N/A
Yamaha	PY64-D	4096	4	N/A	4	N/A	24	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	QL1, QL5 (*5)	64	4	4	4	4	4	4	4	4	N/A	N/A	N/A	N/A
Yamaha	Rio3224-D, Rio1608-D, Ri8-D	32	24	24	32	32	24	24	24	8	N/A	16 (*6)	N/A	8
Yamaha	Ro8-D	32	24	N/A	32	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A
Yamaha	Rio3224-D2, Rio1608-D2	128	24	24	48 (*2)	48 (*2)	24	24	24	8	N/A	16	N/A	8
Yamaha	Rio3224-D3, Rio1608-D3	128	24	24	48 (*2)	48 (*2)	24	24	24	8	N/A	16	N/A	N/A
Yamaha	RSio64-D	32	24	N/A	32	N/A	24	24	24	24	N/A	N/A	N/A	N/A
Yamaha	RMio64-D	16	16	N/A	16	N/A	16	16	16	16	N/A	N/A	N/A	N/A
Yamaha	RUio16-D	32	24	N/A	32	N/A	24	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Yamaha	Tio1608-D	12	12	12	12	12	12	12	12	8	N/A	16	N/A	8
Yamaha	Tio1608-D2	12	12	12	12	12	12	12	12 (*4)	8 (*4)	N/A	16	N/A	8
Yamaha	XMV4140-D, XMV4280-D, XMV8140-D, XMV8240-D	254	24	N/A	48	N/A	24	N/A	24	N/A	N/A	N/A	N/A	N/A

		RIVAGE PM				DM7		CL/QL		DM3		TF	
		per HY card		per system									
Maximum Mountable/HA Controllable Units in Total	-	24	24	48	48	24	24	24	8	N/A	16	N/A	8

*1) Two or more of HY144-D(-SRC) cards are required with RIVAGE PM V5.00 or later.
*2) With RIVAGE PM V5.00 or later. Up to 32 devices with V4.72 or older.
*3) When Shure devices need to be controlled, they must be mounted on the smallest ID of HY144-D(-SRC) card if multiple cards are installed.
*4) When used in Tio1608-D Compatibility Mode, the specifications are the same as for Tio1608-D.
*5) Since DM7/RIVAGE PM HY SLOT/CL/QL do not allow duplicate IDs in the same Dante network while ID 1-4 can be assigned, the total number of mountable units is limited to 3.
*6) Ri8-D does not support DM3 Auto setup.
*7) Due to specification changes in the Focusrite MP8R, the maximum number of controlable units from the CL/QL series is three.

*1) RIVAGE PM V5.00以降且つHY144-D(-SRC)2枚以上挿入時。
*2) RIVAGE PM V5.00以降。V4.72以前は最大32台。
*3) Shureのデバイスをリモートコントロールする場合は、複数のHY144-D(-SRC)挿入されているうち若番のカードにマウントする必要があります。
*4) Tio1608-D Compatibility Modeで使用する場合には、Tio1608-Dと同様の仕様となります。
*5) DM7/RIVAGE PM HY SLOT/CL/QLは同一Danteネットワーク内でIDの重複ができないため、ID設定は1-4が可能ですが、マウントできる台数は合計で3台までです。
*6) Ri8-DはDM3のオートセットアップに対応していません。
*7) Focusrite MP8Rの仕様変更によりCL/QLシリーズからのコントロール台数は最大3台。